An Efficient Implementation of Sigmoidal Neural Nets in Temporal Coding with Noisy Spiking Neurons

Wolfgang Maass

Institute for Theoretical Computer Science
Technische Universitaet Graz
Klosterwiesgasse 32/2
A-8010 Graz, Austria
e-mail: maass@igi.tu-graz.ac.at

Abstract

We show that networks of relatively realistic mathematical models for biological neurons can in principle simulate arbitrary feedforward sigmoidal neural nets in a way which has previously not been considered. This new approach is based on temporal coding by single spikes (respectively by the timing of synchronous firing in pools of neurons), rather than on the traditional interpretation of analog variables in terms of firing rates. The resulting new simulation is substantially faster and hence more consistent with experimental results about the maximal speed of information processing in cortical neural systems.

As a consequence we can show that networks of noisy spiking neurons are "universal approximators" in the sense that they can approximate with regard to temporal coding *any* given continuous function of several variables. This result holds for a fairly large class of schemes for coding analog variables by firing times of spiking neurons.

Our new proposal for the possible organization of computations in networks of spiking neurons systems has some interesting consequences for the type of learning rules that would be needed to explain the self-organization of such networks.

Finally, our fast and noise-robust implementation of sigmoidal neural nets via temporal coding points to possible new ways of implementing feedforward and recurrent sigmoidal neural nets with pulse stream VLSI.

1 Introduction

Sigmoidal neural nets are both for analog and digital parallel computation the most powerful and flexible computational model known today. In addition they have the advantage of allowing "self-organization" via a variety of quite successful learning algorithms. Unfortunately the computational units of sigmoidal neural nets differ strongly from biological neurons, and it is particularly dubious whether sigmoidal neural nets provide a useful paradigm for the organization of *fast* computations in cortical neural systems.

Traditionally one views the firing rate of a neuron as the representation of an analog variable in analog computations with spiking neurons, in particular in the simulation of sigmoidal neural nets by spiking neurons. However with regard to fast cortical computations this view is inconsistent with experimental data. Perrett et al. (Perrett, 1982) and Thorpe et al. (Thorpe, 1989) have demonstrated that visual pattern analysis and pattern classification can be carried out by humans in just 100 ms, in spite of the fact that it involves a minimum of 10 synaptic stages from the retina to the temporal lobe. The same speed of visual processing has been measured by Rolls et al. in macaque monkeys. Furthermore they have shown that a single cortical area involved in visual processing can complete its computation in just 20-30 ms (Rolls, 1994a, 1994b). On the other hand the firing rates of neurons involved in these computations are usually below 100 Hz, and hence at least 20-30 ms would be needed just to sample the current firing rate of a neuron. Thus a coding of analog variables by firing rates is quite dubious in the context of fast cortical computations.

Experimental evidence has accumulated during the last few years which indicates that many biological neural systems use the timing of single action potentials (or "spikes") to encode information (Abeles et al., 1993, Bialek et al., 1992, Bair et al., 1994, Ferster et al., 1995, Hopfield, 1995, Kempter et al., 1996, Sejnowski, 1995, Softky, 1994, Thorpe et al., 1989, Rieke et al., 1996). In addition various experiments have shown that biological neurons are able to fire in vitro with high timing precision (Bryant et al., 1976, Segundo et al., 1994, Mainen and Sejnowski, 1995).

We show in this article that there exists a completely different way of simulating sigmoidal neural nets with spiking neurons that is based on temporal coding with single spikes (respectively on temporal coding by synchronous firings of pools of neurons in a more noise-robust interpretation). This simulation is based on the observation that in the presence of some other excitation which moves the membrane potential close to the firing threshold, individual EPSP's respectively IPSP's (or volleys of synchronized PSP's) are able to *shift* the firing time of a neuron. This mechanism is particularly easy to analyze if we work in a range where all PSP's can be approximated well by linear functions. For this range one can show that the resulting firing

time is linearly related to the *weighted sum* of the firing times of the presynaptic neurons – with the weights corresponding to the *efficacies* ("strengths") of the involved synapses. We will explain this key observation in a bit more detail at the end of this section, after defining the formal model of a noisy spiking neuron. Although this model ignores many of the intricate details of a biological neuron (e.g. nonlinearities in dendritic integration), one may argue that it underestimates, rather than overestimates, the computational capabilities of a biological neuron. We would like to point out that we are not making here explicit *use* of the noise in spiking neurons. Rather we show that the abovementioned computational mechanism is *robust* with respect to various types of noise.

A complementary approach for simulating artificial neural nets by spiking neurons with temporal coding has recently been proposed in (Hopfield, 1995). Hopfield's construction yields basically a simulation of radial basis function ("RBF") units, where the weights of the RBF-units are stored in the *delays* between synapses and soma of a spiking neuron. Hence Hopfield's construction provides an efficient way of implementing a look-up table with spiking neurons (with some very nice invariance regarding the "strength" of the stimulus). However in contrast to the here considered construction his system is based on "grandmother neurons", and it is not geared towards providing an informative output in a situation where the input $\langle s_1, \ldots, s_n \rangle$ does *not* match (up to a factor) one of the *fixed* set of stored patterns (because it is for example a *superposition* of *several* stored patterns). Furthermore Hopfield's construction provides no method for simulating *multi-layer* neural nets. In addition in contrast to our construction it provides no computational or learning related role to the efficacy (i.e. "strength") of synapses between biological neurons.

We will describe in the remainder of this section the precise models for sigmoidal neural nets and noisy spiking neurons that we consider, and we will describe the key mechanism of our simulation at the end of this section. The main construction of this article is given in section 2, and our main result is stated in the Theorem at the end of section 2. In section 3 we show that this result implies that networks of noisy spiking neurons are "universal approximators". We also prove that this result holds for a fairly large class of schemes for temporal coding of analog variables. In section 4 we briefly indicate some new perspectives about the organization of *learning* in biological neural systems which follow from our approach.

We would like to point out that this is not an article about biology, but about computational complexity theory. Its main results (given in section 2 and 3) are rigorous theoretical results about the computational power of common mathemetical models for networks of spiking neurons. However some informal comments have been added (after the Theorem in section 2, as well as in sections 4 and 5) in order to facilitate a discussion of the biological relevance of this mathematical model and its theoretical consequences.

The computational unit of a sigmoidal neural net is a "sigmoidal gate" (or "σ-gate") G, that assigns to analog input numbers $x_1, \ldots, x_{n-1} \in [0, \gamma]$ an output of the form $\sigma(\sum_{i=1}^{n-1} r_i \cdot x_i + r_n)$. The function $\sigma : \mathbf{R} \to [0, \gamma]$ is called the *activation function* of G, $r_1, \ldots, r_{n-1}$ are the "weights" of G , and r_n is the "bias" of G . The latter are thought to be *adjustable* parameters of G in the context of a learning process. The parameter $\gamma > 0$ determines the "scale" of the analog computations carried out by the neural net.

For convenience we assume that each σ-gate G has an additional input x_n with some constant value $c \in (0, \gamma]$ available. Hence after rescaling r_n the function f_G that is computed by G can be viewed as a restriction of the function

$$f_G(x_1, \ldots, x_n) \;=\; \sigma\left(\sum_{i=1}^{n} r_i \cdot x_i\right)$$

to arguments with $x_n = c$. The original choice for the activation function σ in (Rumelhart et al., 1986) has been the "logistic sigmoid function" $\sigma(y) = 1/(1 + e^{-y})$. Many years of practical experience with sigmoidal neural nets have shown that the exact form of the activation function σ is not relevant for the computational power and learning capabilities of such neural nets, as long as σ is non-decreasing and almost everywhere differentiable, the limits $\lim_{y \to -\infty} \sigma(y)$ and $\lim_{y \to \infty} \sigma(y)$ have finite values, and σ increases approximately linearly in some intermediate range. Gradient-descent learning procedures such as backprop formally require that σ is *everywhere* differentiable, but practically one can use just as well the piecewise linear "linear saturated" activation function $\pi_\gamma : \mathbf{R} \to [0, \gamma]$ defined by

$$\pi_\gamma(y) = \begin{cases} 0\,, & \text{if} \quad y < 0 \\ y\,, & \text{if} \quad 0 \leq y \leq \gamma \\ \gamma\,, & \text{if} \quad y > \gamma \end{cases} \qquad .$$

As a model for a spiking neuron we take the common model of a *leaky integrate and fire neuron with noise*, respectively the somewhat more general *spike response model* of (Gerstner, van Hemmen, 1994). The only specific assumption that is needed for the construction in this article is that postsynaptic potentials can be described (respectively approximated) by a linear function during some initial segment. Actually, the constructions of this article appear to be of interest even if this assumption is not satisfied, but in this case they are harder to analyze theoretically.

We consider networks that consist of a finite set V of *spiking neurons*, a set $E \subseteq V \times V$ of *synapses*, a *weight* $w_{u,v} \geq 0$ and a *response function* $\varepsilon_{u,v} : \mathbf{R}^+ \to \mathbf{R}$ for each synapse $\langle u, v \rangle \in E$ (where $\mathbf{R}^+ := \{x \in \mathbf{R} : x \geq 0\}$), and a *threshold function* $\Theta_v : \mathbf{R}^+ \to \mathbf{R}^+$ for each neuron $v \in V$.

Each response function $\varepsilon_{u,v}$ models either an excitatory postsynaptic potential (EPSP), or an inhibitory postsynaptic potential (IPSP). The typical shape of EPSP's and IPSP's is indicated in Figure 1.



Figure1: The typical shape of inhibitory and excitatory postsynaptic potentials at a biological neuron (we assume that the resting membrane potential has the value 0)

If $F_u \subseteq \mathbf{R}^+$ is the set of *firing times* of a neuron u, then the *potential* at the trigger zone of neuron v at time t is given by

$$P_v(t) := \sum_{u:\langle u,v\rangle \in E} \sum_{s \in F_u : s<t} w_{u,v} \cdot \varepsilon_{u,v}(t-s) \qquad .$$

Furthermore one considers a threshold function $\Theta_v(t-t')$ that quantifies the "reluctance" of v to fire again at time t, if its last previous firing was at time t'. Thus $\Theta_v(x)$ is extremely large for small x, and then approaches $\Theta_v(0)$ for larger x. In a noise-free model a neuron v fires at time t as soon as $P_v(t)$ reaches $\Theta_v(t-t')$.

The form of this threshold function Θ_v is not important for the constructions in this article, since we consider here only computations that rely on the timing of the *first* spike in a spike train. Thus it suffices to assume that $\Theta_v(t-t') = \Theta_v(0)$ for sufficiently large values of $t-t'$, and that $\inf\{\Theta_v(x) : x \in (0,\gamma]\}$ is larger than the potentials $P_v(t)$ that occur in the construction of section 2 for $t \in [T_{out}-\gamma, T_{out}]$. The latter condition (which amounts to the assumption of a sufficiently long absolute, respectively relative refractory period) will prevent *iterated* firing of neuron v during the critical time interval $[T_{out}-\gamma, T_{out}]$.

Our construction in section 2 is robust with respect to several types of noise that make the model of a spiking neuron biologically more realistic. As in the model for a leaky integrate and fire neuron with noise we allow that the potentials $P_v(t)$ and the threshold functions $\Theta_v(t-t')$ are subject to some additive noise. Hence $P_v(t)$ is replaced by

$$P_v^{noisy}(t) := P_v(t) + \alpha_v(t)$$

and $\Theta_v(t-t')$ is replaced by

$$\Theta_v^{noisy}(t-t') := \Theta_v(t-t') + \beta_v(t) \ ,$$

where $\alpha_v(t)$ and $\beta_v(t)$ describe the impact of some unknown (or even adversarial) source of noise (which might for example result from synapse-failures).

One assumes in most previous theoretical studies that $\alpha_v(t)$, $\beta_v(t)$ are distributed according to some specific probability distribution (e.g. "white noise"), whereas our subsequent constructions allow that $\alpha_v(t)$, $\beta_v(t)$ are some *arbitrary* functions with bounded absolute value (e.g. "systematic noise").

In a *simpler* model for a noisy spiking neuron one assumes that a neuron v fires exactly at those time points t when $P_v^{noisy}(t)$ reaches from below the value $\Theta_v^{noisy}(t - t')$. We consider in this article a biologically more realistic model, where as in (Gerstner, van Hemmen, 1994) the size of the difference $P_v^{noisy}(t) - \Theta_v^{noisy}(t - t')$ just governs the *probability* that neuron v fires. The choice of the exact firing times is left up to some unknown stochastic processes, and it may for example occur that v does *not* fire in a time interval I during which $P_v^{noisy}(t) - \Theta_v^{noisy}(t - t') > 0$, or that v fires "spontaneously" at a time t when $P_v^{noisy}(t) - \Theta_v^{noisy}(t - t') < 0$.

The only assumption that we need for our subsequent construction about the firing mechanism is that for any time interval I of length > 0 the probability that v fires during I is arbitrarily close to 1 (respectively 0) if $P_v^{noisy}(t) - \Theta_v^{noisy}(t - t')$ is sufficiently large (respectively sufficiently strongly negative) for all $t \in I$ (up to the time when v fires).

It turns out that it suffices to assume only the following rather weak properties of the response functions $\varepsilon_{u,v}$:

Each response function $\varepsilon_{u,v} : \mathbf{R}^+ \to \mathbf{R}$ is either excitatory or inhibitory. All *excitatory* response functions $\varepsilon_{u,v}(t)$ have the value 0 for $t \in [0, d_{u,v}]$, and the value $t - d_{u,v}$ for $t \in [d_{u,v}\,, d_{u,v} + \triangle]$, where $d_{u,v} \geq 0$ is some fixed "delay" and $\triangle > 0$ is some other constant. Furthermore we assume that $\varepsilon_{u,v}(t) \geq \varepsilon_{u,v}(d_{u,v} + \triangle)$ for all $t \in [d_{u,v} + \triangle\,, d_{u,v} + \triangle + \gamma]$, where γ with $0 < \gamma \leq \triangle/2$ is another constant.

With regard to *inhibitory* response functions $\varepsilon_{u,v}(t)$ we assume that $\varepsilon_{u,v}(t) = 0$ for $t \in [0, d_{u,v}]$, and $\varepsilon_{u,v}(t) = -(t - d_{u,v})$ for $t \in [d_{u,v}\,, d_{u,v} + \triangle]$. Furthermore we assume that $\varepsilon_{u,v}(t) = 0$ for all sufficiently large t .

Finally we need a mechanism for "increasing" the firing threshold $\Theta := \Theta_v(0)$ of a "rested" neuron v (at least for a short period). One biologically plausible assumption which would account for such increase is that neuron v receives a large number of IPSP's from randomly firing neurons that arrive on synapses that are far away from the trigger zone of v, so that each single one of them has hardly any effect on the dynamics of the potential at the trigger zone, but together they contribute a rather steady negative summand BN^- to the potential at the trigger zone. Other possible explanations for the increase of the firing threshold Θ could be based on the con-

tribution of inhibitory interneurons whose IPSP's arrive close to the soma and are time-locked to the onset of the stimulus, or on "spike adaption" respectively $GABA_B$ currents.

Formally we assume that each neuron v receives some negative (i.e. "inhibitory") potential $BN^- < 0$ that can be assumed to be constant during the time intervals that are considered in the following.

In comparison with other models for spiking neurons, this model is with regard to the types of noise that it allows more general than the models considered in (Gerstner, van Hemmen, 1994, and Maass, 1995). On the other hand this model is somewhat less general than the one considered in (Maass, 1996a).

After having defined our formal model, we can now explain the *key mechanism* of our constructions in a bit more detail. It is well-known that incoming EPSP's and IPSP's are able to *shift* the firing time of a biological neuron. We explore this effect in the mathematical model of a spiking neuron, and show that it can in principle be used to carry out complex analog computations in temporal coding. Assume that a spiking neuron v receives PSP's from presynaptic neurons $a_1, \ldots, a_n$, that w_i is the "weight" (efficacy) for the synapse from a_i to v , and that d_i is the time delay from a_i to v . Then there exists a range of values for the parameters where the firing time t_v of neuron v can be written in terms of the firing times t_{a_i} of the presynaptic neurons a_i as

$$t_v \quad = \quad \frac{\Theta - BN^-}{\sum_{i=1}^n w_i} \quad + \quad \frac{\sum_{i=1}^n w_i \cdot (t_{a_i} + d_i)}{\sum_{i=1}^n w_i} \quad . \tag{1}$$

Hence a spiking neuron is in principle able to *compute* in *temporal coding* of inputs and outputs a *linear function* (where the efficacies of synapses encode the coefficients of the linear function, like in rate coding of analog variables). The calculations at the beginning of section 2 show that this holds precisely if there is no noise and the n PSP's are at time t_v all in their initial linearly rising (respectively linearly decreasing) phase. However for a biological interpretation it is interesting to know that even if the firing times t_{a_i} (respectively their "effective values" $t_{a_i} + d_i$) lie further apart, this mechanism computes a meaningful approximation to a linear function. It employs (through the natural shape of PSP's) an interesting adaptation of "outliers" among the $t_{a_i} + d_i$: input neurons a_i that fire too late (relative to the average) loose their influence on the determination of t_v , and input neurons a_i that fire extremely early have the same impact as neurons a_i that fire somewhat later (but still before the average). We refer to Remark 2. in section 2 for a more detailed discussion of this effect.

The goal of the next section is to prove a rigorous theoretical result about the computational power of formal models for networks of spiking neurons. We are not claiming that this construction (which is designed exclusively for that purpose) pro-

vides a "blueprint" for the organization of fast analog computations in biological neural systems. However is provides the first theoretical model which is able to explain the possibility of fast analog computations with noisy spiking neurons. Some remarks about the possible biological relevance of details of this construction can be found after the Theorem in section 2.

2 The Main Construction

Consider an arbitrary π_γ-gate G, for some $\gamma > 0$, which computes a function $f_G : [0,\gamma]^n \to [0,\gamma]$. Let $r_1, \ldots, r_n \in \mathbf{R}$ be the weights of G. Thus we have

$$f_G(s_1,\ldots,s_n) = \begin{cases} 0 & , \text{ if } \sum_{i=1}^n r_i \cdot s_i < 0 \\ \sum_{i=1}^n r_i \cdot s_i & , \text{ if } 0 \le \sum_{i=1}^n r_i \cdot s_i \le \gamma \\ \gamma & , \text{ if } \sum_{i=1}^n r_i \cdot s_i > \gamma \end{cases}$$

for arbitrary inputs $s_1, \ldots, s_n \in [0,\gamma]$.

For the sake of simplicity we will first consider the case of spiking neurons *without* noise (i.e. $\alpha_v = \beta_v \equiv 0$ and each neuron v fires whenever $P_v(t)$ crosses $\Theta_v(t-t')$ from below). Afterwards we will describe the changes that are needed in this construction for the general case of noisy spiking neurons.

We construct for a given π_γ-gate G and for an arbitrary given parameter $\varepsilon > 0$ with $\varepsilon < \gamma$ a network $\mathcal{N}_{G,\varepsilon}$ of spiking neurons that approximates f_G with precision $\le \varepsilon$, i.e. the output $\mathcal{N}_{G,\varepsilon}(s_1,\ldots,s_n)$ of $\mathcal{N}_{G,\varepsilon}$ satisfies $|\mathcal{N}_{G,\varepsilon}(s_1,\ldots,s_n) - f_G(s_1,\ldots,s_n)| \le \varepsilon$ for all $s_1,\ldots,s_n \in [0,\gamma]$.

In order to be able to scale the size of "weights" according to the given gate G we assume that $\mathcal{N}_{G,\varepsilon}$ receives an additional input s_0 which is given like the other input variables $s_1,\ldots,s_n$ in temporal coding. Thus we assume that there are $n+1$ input neurons $a_0,\ldots,a_n$ with the property that a_i fires at time $T_{in} - s_i$ (where T_{in} is some constant). We will discuss at the end of this section (in Remarks 5. and 6.) biologically more plausible variations of our construction where a_0 and T_{in} are not needed.

We construct a spiking neuron v in $\mathcal{N}_{G,\varepsilon}$ that receives $n+1$ PSP's $h_0(t),\ldots,h_n(t)$ from the $n+1$ input neurons $a_0,\ldots,a_n$, which result from the firing of a_i at time $T_{in} - s_i$.

In addition v receives some auxiliary PSP's from other spiking neurons in $\mathcal{N}_{G,\varepsilon}$, whose timing depends only on T_{in} .



Figure 2: Illustration regarding the simulation of a sigmoidal gate by a spiking neuron v in temporal coding

The firing time t_v of this neuron v will provide the output $\mathcal{N}_{G,\varepsilon}(s_1, \ldots, s_n)$ of the network $\mathcal{N}_{G,\varepsilon}$ in temporal coding, i.e. v will fire at time $T_{out} - \mathcal{N}_{G,\varepsilon}(s_1, \ldots, s_n)$ for some T_{out} that does not depend on $s_1, \ldots, s_n$. Let $w_{a_i,v}$ be the weight of the synapse from input neuron a_i to neuron v, $i = 0, \ldots, n$. We assume that the "delay" $d_{a_i,v}$ between a_i and v is the same for all input neurons $a_0, \ldots, a_n$, and we write d for this common delay. Thus we can describe for $i = 0, \ldots, n$ the impact of the firing of a_i at time $T_{in} - s_i$ on the potential at the trigger zone of neuron v at time t by the EPSP or IPSP $h_i(t) = w_{a_i,v} \cdot \varepsilon_{a_i,v}(t - (T_{in} - s_i))$, which has on the basis of our assumptions the value

$$h_i(t) = \begin{cases} 0 & , \quad \text{if} \quad t - (T_{in} - s_i) < d \\ w_i \cdot (t - (T_{in} - s_i) - d) & , \quad \text{if} \quad d \leq t - (T_{in} - s_i) \leq d + \Delta \end{cases} ,$$

where $w_i = w_{a_i,v}$ in the case of an EPSP and $w_i = -w_{a_i,v}$ in the case of an IPSP.

We assume that neuron v has not fired for a sufficiently long time, so that its threshold function $\Theta_v(t - t')$ can be assumed to have a constant value Θ when the

PSP's $h_0(t), \ldots, h_n(t)$ arrive at the trigger zone of v. Furthermore we assume for the moment that besides these $n+1$ PSP's only BN^- influences the potential at the trigger zone of v. This contribution BN^- is assumed to have a constant value in the here considered time-interval. Then if no noise is present, the time t_v of the next firing of v can be described by the equality

$$\Theta = \sum_{i=0}^{n} h_i(t_v) + BN^- \;=\; \sum_{i=0}^{n} w_i \cdot (t_v - (T_{in} - s_i) - d) + BN^- \quad , \tag{2}$$

provided that

$$d \leq t_v - (T_{in} - s_i) \leq d + \Delta \;\text{ for }\; i \;=\; 0, \ldots, n \quad . \tag{3}$$

We assume from now on that a fixed value $s_0 \equiv 0$ is chosen for the extra input s_0. Then (2) is equivalent to

$$t_v \;=\; \frac{\Theta - BN^-}{\sum_{i=0}^{n} w_i} \;+\; T_{in} \;+\; d \;-\; \frac{\sum_{i=1}^{n} w_i \cdot s_i}{\sum_{i=0}^{n} w_i} \quad . \tag{4}$$

This t_v satisfies (3) if $-s_j \;\leq\; t_v - T_{in} - d \;\leq\; \Delta - s_j$ for $j = 0, \ldots, n$, hence for any $s_j \in [0, \gamma]$ if

$$0 \;\leq\; \frac{\Theta - BN^- - \sum_{i=1}^{n} w_i \cdot s_i}{\sum_{i=0}^{n} w_i} \;\leq\; \Delta - \gamma \quad . \tag{5}$$

We set $w_i := \lambda \cdot r_i$ for $i = 1, \ldots, n$, where $r_1, \ldots, r_n$ are the weights of the simulated π_γ-gate G, and $\lambda > 0$ is some not yet determined factor (that we will later choose sufficiently large in order to make sure that neuron v fires closely to the time t_v given by (4) even in the presence of noise). We choose w_0 so that $\sum_{i=0}^{n} w_i = \lambda$. This implies that (4) with

$$T_{out} := \frac{\Theta - BN^-}{\lambda} + T_{in} + d$$

is now equivalent to

$$t_v \;=\; T_{out} - \sum_{i=1}^{n} r_i \cdot s_i \quad , \tag{6}$$

and (5) is equivalent to

$$0 \;\leq\; \frac{\Theta - BN^-}{\lambda} \;- \sum_{i=1}^{n} r_i \cdot s_i \;\leq\; \Delta - \gamma \quad . \tag{7}$$

Hence, provided that γ , λ and BN^- are chosen in relationship to Θ and Δ so that

$$\gamma \;\leq\; \frac{\Theta - BN^-}{\lambda} \;\leq\; \Delta - \gamma \quad , \tag{8}$$

we have satisfied (5), and therefore achieved that the firing time t_v of neuron v provides in temporal coding the output $f_G(s_1,\ldots,s_n) = \sum_{i=1}^n r_i \cdot s_i$ of the simulated π_γ-gate G for all inputs $s_1,\ldots,s_n \in [0,\gamma]$ with $\sum_{i=1}^n r_i \cdot s_i \in [0,\gamma]$.

In order to simulate G also for $s_1,\ldots,s_n \in [0,\gamma]$ with other values of $\sum_{i=1}^n r_i \cdot s_i$, we make sure that v fires at a time with distance at most ε to $T_{out}-\gamma$ if $\sum_{i=1}^n r_i \cdot s_i$ is larger than γ, and that v fires with distance at most ε to time T_{out} if $\sum_{i=1}^n r_i \cdot s_i < 0$. For that purpose we add inhibitory and excitatory neurons which fire at times that depend on time T_{in}, but not on the input $s_1,\ldots,s_n$. The activity of these auxiliary inhibitory and excitatory neurons may also shift the firing time t_v of v if $\sum_{i=1}^n r_i \cdot s_i \in [0,\gamma]$, but at most by ε.

According to the previously described construction we have by (6) that $t_v = T_{out}$ if $s_i = 0$ for $i = 1,\ldots,n$ (and therefore $\sum_{i=1}^n r_i \cdot s_i = 0$). Furthermore the parameters have been chosen so that (3) is satisfied for this case, which implies that each of the PSP's $h_i(t)$ is at time T_{out} for $s_i = 0$ still within the initial segment of length Δ of its first non-zero segment. This implies that for *any* value of $s_i \in [0,\gamma]$ the PSP $h_i(t)$ is at time $T_{out}-\gamma$ not further advanced than the end of the initial segment of length Δ of its first non-zero segment. Thus

$$|h_i(t)| = |w_i \cdot (t-(T_{in}-s_i)-d)| \;\le\; |w_i| \cdot (T_{out}-\gamma-(T_{in}-\gamma)-d) \;\le\; |w_i| \cdot \Delta$$

for all $t \le T_{out}-\gamma$ and all $s_i \in [0,\gamma]$. This implies that for *any* $s_1,\ldots,s_n \in [0,\gamma]$ (even if $\sum_{i=1}^n r_i \cdot s_i \notin [0,\gamma]$) we have $|\sum_{i=0}^n h_i(t)| \le W \cdot \Delta$ for all $t \le T_{out}-\gamma$, where $W := \sum_{i=0}^n |w_i|$.

Hence in order to prevent a firing of v before time $T_{out}-\gamma$, it suffices to employ auxiliary neurons in $\mathcal{N}_{G,\varepsilon}$ which send IPSP's to v that lower the potential at the trigger zone of v during the interval $[T_{out}-\gamma-\Delta\,,\,T_{out}-\gamma]$ by more than $W\cdot\Delta+BN^- -\Theta$. In general these IPSP's will also influence the potential at the trigger zone of v shortly *after* time $T_{out}-\gamma$. Since these auxiliary IPSP's will be independent of the input $s_1,\ldots,s_n$, they may delay the firing of v even in the case where $\sum_{i=1}^n r_i \cdot s_i \in [0,\gamma]$. In order to approximate the given π_γ-gate G with an error of at most ε , we assume that these auxiliary IPSP's have vanished at the trigger zone of v by time $T_{out}-\gamma+\varepsilon$. It is obvious that all these conditions can be achieved with a sufficient number (and/or "weights") of auxiliary synchronized IPSP's from inhibitory neurons in $\mathcal{N}_{G,\varepsilon}$ whose firing time depends only on T_{in}. This can be satisfied using only the very weak condition that each IPSP is continuous and of value $\neq 0$ before it eventually vanishes (see our precise condition in section 1).

We now want to make sure that v fires at the latest by time $T_{out}-\gamma+\varepsilon$ if $\sum_{i=1}^n r_i \cdot s_i > \gamma-\varepsilon$. Since all auxiliary IPSP's have vanished by time $T_{out}-\gamma+\varepsilon$, we have $P_v(T_{out}-\gamma+\varepsilon) = \sum_{i=0}^n h_i(T_{out}-\gamma+\varepsilon) + BN^-$. Hence it suffices to show that the latter is $\ge \Theta$. Consider the set I of those $i \in \{1,\ldots,n\}$ with $r_i > 0$, i.e.

those i where $w_{a_i,v} \cdot \varepsilon_{a_i,v}(t)$ represents an EPSP. By choosing suitable values s'_i in the interval $[0, s_i]$ for $i \in I$ and by setting $s'_i := s_i$ for $i \in \{1, \ldots, n\} - I$, one can achieve that $\sum_{i=1}^{n} r_i \cdot s'_i = \gamma - \varepsilon$. According to (6) the potential P_v reaches the value Θ at time $T_{out} - \gamma + \varepsilon$ for the input $\langle s'_1, \ldots, s'_n \rangle$, and according to (3), (5), (7), (8) each PSP $w_{a_i,v} \cdot \varepsilon_{a_i,v}$ is at time $T_{out} - \gamma + \varepsilon$ still within Δ of the beginning of its non-zero phase. If one now changes s'_i to s_i for $i \in I$, the EPSP $w_{a_i,v} \cdot \varepsilon_{a_i,v}$ will be advanced in time by $s_i - s'_i \in [0, \gamma]$. Hence each of the EPSP's $w_{a_i,v} \cdot \varepsilon_{a_i,v}$ for $i \in I$ is for input s_i at time $T_{out} - \gamma + \varepsilon$ within $\Delta + \gamma$ of the beginning of its rising phase. Since we have assumed in section 1 that $w_{a_i,v} \cdot \varepsilon_{a_i,v}(t) \geq w_{a_i,v} \cdot \varepsilon_{a_i,v}(d + \Delta)$ for all $t \in [d + \Delta, d + \Delta + \gamma]$, $P_v(T_{out} - \gamma + \varepsilon)$ has for input $\langle s_1, \ldots, s_n \rangle$ a value that is at least as large as for input $\langle s'_1, \ldots, s'_n \rangle$, and therefore a value $\geq \Theta$. This implies that in the case $\sum_{i=1}^{n} r_i \cdot s_i > \gamma - \varepsilon$ the neuron v will fire within the time interval $[T_{out} - \gamma \, , T_{out} - \gamma + \varepsilon]$.

In an analogous manner we can achieve with the help of EPSP's from auxiliary excitatory neurons in $\mathcal{N}_{G,\varepsilon}$ (whose firing time depends only on T_{in}, not on the input values $s_1, \ldots, s_n$) that neuron v fires at the latest at time T_{out}, even if $\sum_{i=1}^{n} r_i \cdot s_i < 0$. The preceding analysis implies that for any value $s_i \in [0, \gamma]$ and any $t \leq T_{out}$ the absolute value of the PSP $w_{a_i,v} \cdot \varepsilon_{a_i,v}(t)$ can be bounded by $|w_{a_i,v}| \cdot \rho$, where $\rho := \sup\{|\varepsilon_{a_i,v}(t)| : i \in \{0, \ldots, n\} \text{ and } t \in [d \, , d + \Delta + \gamma]\}$ is the maximum absolute value that any $\varepsilon_{a_i,v}(t)$ for $i = 0, \ldots, n$ can reach during the initial segment of length $\Delta + \gamma$ of its non-zero segment. Thus if the absolute value of these functions $\varepsilon_{a_i,v}(t)$ grows during $[d + \Delta, d + \Delta + \gamma]$ not faster than during their linear segment $[d, d + \Delta]$ (which apparently holds for biological PSP's), we can set $\rho := \Delta + \gamma$. Consequently we can derive for any $t \leq T_{out}$ and any values $s_1, \ldots, s_n \in [0, \gamma]$ the bound $|\sum_{i=0}^{n} h_i(t)| \leq \sum_{i=0}^{n} |w_{a_i,v}| \cdot \rho = W \cdot \rho$. Thus it suffices to make sure that EPSP's from auxiliary neurons in $\mathcal{N}_{G,\varepsilon}$ reach the trigger zone of neuron v shortly after time $T_{out} - \varepsilon$, and that their sum reaches a value $\Theta - BN^- + W \cdot \rho$ by time T_{out}. Then for any values of $s_1, \ldots, s_n \in [0, \gamma]$ the potential $P_v(t)$ will reach the value Θ at the latest by time T_{out}, causing a firing of v by time T_{out} . These auxiliary EPSP's will in general have the side-effect that they slightly advance for inputs $s_1, \ldots, s_n \in [0, \gamma]$ with $\sum_{i=1}^{n} r_i \cdot s_i \in [0, \varepsilon]$ the firing time t_v , but the firing time will stay *within* the interval $[T_{out} - \varepsilon, T_{out}]$.

According to our assumption in section 1 $\inf\{\Theta_v(x) : x \in (0, \gamma]\}$ is so large that v cannot fire *more* than once during $[T_{out} - \gamma \, , T_{out}]$. Hence our construction makes sure that v fires *exactly once* during $[T_{out} - \gamma \, , T_{out}]$ for any inputs $s_1, \ldots, s_n \in [0, \gamma]$. In the following we will denote this firing time t_v of v by $T_{out} - \mathcal{N}_{G,\varepsilon}(s_1, \ldots, s_n)$.

We have now shown that under the assumption that no noise influences the firing time t_v of neuron v , we have $|\mathcal{N}_{G,\varepsilon}(s_1, \ldots, s_n) - f_G(s_1, \ldots, s_n)| \leq \varepsilon$ for all $s_1, \ldots, s_n \in [0, \gamma]$. If one plots the variable $y = \mathcal{N}_{G,\varepsilon}(s_1, \ldots, s_n)$ which neuron v outputs in temporal coding as a function of $\sum_{i=1}^{n} r_i \cdot s_i$, one sees that the effective "activation function" σ of this implementation of the π_γ-gate G has the form indicated in Figure

3:



Figure 3: The resulting "activation function" σ of the implementation of a sigmoidal gate in temporal coding.

Like the piecewise linear activation function π_γ of the simulated gate G, this activation function σ is linear in the intervals $(-\infty, 0]$, $[\varepsilon, \gamma - \varepsilon]$, $[\gamma, \infty)$. However in contrast to π_γ it connects these linear segments by smooth segments in the intervals $[0, \varepsilon]$ and $[\gamma - \varepsilon, \gamma]$, whose precise shape depends on the exact shape and size of the previously discussed auxiliary EPSP's and IPSP's.

We will now consider the general case where the firing time t_v of v is subject to two types of *noise*, as described in section 1. We show that by choosing the parameter λ in our preceding construction sufficiently large, we can achieve that in spite of these two types of noise the actual firing time $\tilde{t}_v$ of neuron v will be arbitrarily close to the previously considered "deterministic firing time" t_v of neuron v, with probability arbitrarily close to 1.

Assume that some arbitrary $\varepsilon, \delta > 0$ are given. In the preceding construction we had chosen values $w_i := \lambda \cdot r_i$ for the strengths of the synapses to neuron v, where $\lambda > 0$ was some not yet determined factor. According to (4) a change in the value of this parameter λ can only result in a shift of t_v by an amount that is independent from the input variables $s_1, \ldots, s_n$. Furthermore if one chooses the contribution BN^- of inhibitory background noise in dependence of λ so that $\Theta - BN^- = \lambda \cdot \tilde{c}$ for some constant $\tilde{c}$, the resulting firing time t_v is completely independent from the choice of λ . On the other hand the parameter λ occurs as a factor in the non-constant term $\sum_{i=0}^{n} \lambda \cdot r_i \cdot |\varepsilon_{a_i,v}(t - (T_{in} - s_i))| = \sum_{i=0}^{n} h_i(t)$ in the potential $P_v(t) = \sum_{i=0}^{n} h_i(t) + BN^-$ (we ignore the effect of auxilary PSP's for the moment). Hence by choosing λ sufficiently large one can make sure that in the deterministic case $P_v(t)$ has an arbitrarily large derivative at the time t_v when it crosses $\Theta_v(t - t')$.

Furthermore if we choose γ, λ , and BN^- so that (8) can be replaced by

$$2\gamma \;\leq\; \frac{\Theta - BN^-}{\lambda} \;\leq\; \triangle - \gamma - \varepsilon \;\;, \tag{9}$$

then it is guaranteed that the linearly increasing potential $P_v(t)$ (with slope proportional to λ) will rise with the same slope throughout the interval $[t_v - \gamma\,, t_v + \varepsilon]$.

If we now keep this setting of the parameters, but replace the deterministic neuron v by a stochastic neuron v that is subject to the two types of noise that were specified in section 1, the following can be observed. If $|\alpha(t)| \leq \alpha$ and $|\beta(t)| \leq \beta$ for all t , then the time interval around t_v during which $P_v(t)$ is within the interval $[\Theta - \alpha - \beta\,, \Theta + \alpha + \beta]$ becomes arbitrarily small for sufficiently large λ .

Furthermore if λ is sufficiently large (and BN^- is adjusted along with λ so that $\frac{\Theta - BN^-}{\lambda} = \tilde{c}$ for some constant $\tilde{c} > 0$ that is independent of λ), then $P_v(t) + \alpha + \beta - \Theta$ is arbitrarily negative during $[T_{out} - \gamma\,,\, t_v - \varepsilon]$. Thus the probability that v fires during $[T_{out} - \gamma\,,\, t_v - \varepsilon]$ can be brought arbitrarily close to 0. In addition, by making λ sufficiently large one can achieve that $P_v(t) - \alpha - \beta - \Theta$ is arbitrarily large throughout the time interval $[t_v + \varepsilon/2\,,\, t_v + \varepsilon]$. Hence the probability that v fires by time $t_v + \varepsilon$ can be brought arbitrarily close to 1.

If one increases the number (respectively weights) of the previously described auxilary PSP's in an analogous manner, one can achieve for the here considered noisy neuron model that with probability $\geq 1 - \delta$ the neuron v of the here constructed network $\mathcal{N}_{G,\varepsilon,\delta}$ fires exactly once during $[T_{out} - \gamma\,,\, T_{out}]$, and at a time $\tilde{t}_v = T_{out} - \mathcal{N}_{G,\varepsilon,\delta}(s_1, \ldots, a_n)$ with $|\mathcal{N}_{G,\varepsilon,\delta}(s_1, \ldots, a_n) - f_G(s_1, \ldots, s_n| \leq 2\varepsilon$, for all $s_1, \ldots, s_n \in [0, \gamma]$.

The previously described construction can easily be adapted to allow shifts in the arrival times of auxiliary PSP's at v of up to $\varepsilon/2$. Hence we can allow that these PSP's also come from *noisy* spiking neurons.

In order to simulate an arbitrary given feedforward network N of π_γ-gates with precision ε and probability $\geq 1 - \delta$ of correctness, one applies the preceding construction separately to each gate G in N. For any given $\varepsilon, \delta > 0$ one determines for each π_γ-gate G in N (starting at the output gates of N) suitable values $\varepsilon_G, \delta_G > 0$, so that in order to approximate N within ε with probability $\geq 1 - \delta$ it suffices that each gate G in N is approximated within $2\varepsilon_G$ with probability $\geq 1 - \delta_G$ by a network $\mathcal{N}_{G,\varepsilon_G,\delta_G}$ of noisy spiking neurons. In this way one can achieve that the network $\mathcal{N}_{N,\varepsilon,\delta}$ of noisy spiking neurons that is composed of these networks $\mathcal{N}_{G,\varepsilon_G,\delta_G}$ approximates in temporal coding with probability $\geq 1 - \delta$ the output of N within ε , for any given network input $x_1, \ldots, x_m \in [0, \gamma]$. Actually it would be more efficient if the modules $\mathcal{N}_{G,\varepsilon_G,\delta_G}$ are not disjoint, but share the neurons which generate the auxiliary EPSP's and IPSP's. On the side we would like to point out that the problem of achieving reliable digital and analog computation with noisy neurons had already been considered

in (von Neumann, 1956) for other types of formal neuron models.

Thus we have shown:

Theorem: *For any given $\varepsilon, \delta > 0$ one can simulate any given feedforward sigmoidal neural net N consisting of π_γ − gates (for some sufficiently small γ that depends on the chosen model for a spiking neuron) by a network $\mathcal{N}_{N,\varepsilon,\delta}$ of noisy spiking neurons in temporal coding. More precisely, for any network input $x_1, \ldots, x_m \in [0, \gamma]$ the output of $\mathcal{N}_{N,\varepsilon,\delta}$ differs with probability $\geq 1 - \delta$ by at most ε from that of N .*

Furthermore the computation time of $\mathcal{N}_{N,\varepsilon,\delta}$ depends neither on the number of gates in N nor on the parameters ε, δ , but only on the number of layers of the sigmoidal neural network N .

Remarks:

1. One can exploit the concrete shape of PSP's in biological neurons in order to arrive at an alternative approximation of sigmoidal neural nets by spiking neurons in temporal coding *without* simulating explicity the activation function π_γ of the sigmoidal neural net. In this alternative approach one can *delete* from the previously described construction the auxiliary neurons that prevent a firing of neuron v before time $T_{out} - \gamma$, and which force it to fire at the latest by time T_{out} . Furthermore in this interpretation we no longer have to assume that the initial linear segments of all incoming PSP's overlap, and hence less precision in the firing times is needed.

   In case that v fires substantially *after* time T_{out} , the resulting PSP at a postsynaptic neuron v' (which simulates a sigmoidal gate on the *next* layer of the simulated sigmoidal neural net) has at the time $t_{v'}$ when v' fires still its initial value 0 . Dually, if v fires *before* time $T_{out} - \gamma$, the resulting PSP may be at time $t_{v'}$ already near its saturation value (where it increases respectively decreases more slowly than during its initial "linear phase"). Thus in either case the concrete functional form of EPSP's and IPSP's in a biological neuron v' modulates the input from a presynaptic neuron v in a way which corresponds to the application of a "saturating" sigmoidal activation function to the output of v in temporal coding. Furthermore larger differences than γ between the firing times of presynaptic neurons v can be tolerated in this context.

   This *implicit* implementation of an activation function is however mathematically not precise: a closer look shows that the amount by which the output of v in temporal coding is "adjusted" depends on the size of the output of v *relative* to the size of the outputs of the *other* presynaptic neurons of v' (in temporal coding). The output of v is changed by a larger amount if it differs more strongly from the median output of the other presynaptic neurons of v' (but

it is always moved in the direction of the median). This "context dependent" modulation of the output of v is hard to exploit for precise theoretical results, but it appears to be useful for practically relevant computations such as pattern recognition.

Thus we arrive in this way at a variation of the implementation of a sigmoidal neural net, where two biologically dubious components of our main construction (the auxiliary neurons which force v to fire exactly once during $[T_{out}-\gamma, T_{out}]$, as well as the requirement that the initial linear segments of all relevant PSP's have to overlap) are deleted, but the resulting network of spiking neurons can still carry out complex and practically useful multi-layer computations in temporal coding.

2. Our construction shows as a special case that a *linear* function of the form $\underline{s} \mapsto \underline{w} \cdot \underline{s}$ for real-valued inputs $\underline{s} = \langle s_1, \ldots, s_n \rangle$ and a stored vector $\underline{w} = \langle w_1, \ldots, w_n \rangle$ can be computed very efficiently (and very fast) by a spiking neuron v in temporal coding. In this case no auxiliary neurons are needed.

   A fast computation of linear functions is obviously relevant in many biological contexts, such as coordinate transformations between different frames of reference, or the analysis of a complex stimulus $\underline{s}$ in terms of many stored patterns $\underline{w}, \underline{w}', \ldots$.

   For example in an olfactory neural system (see e.g. Hopfield, 1991, 1995) the stimulus $\underline{s}$ may be thought of as a superposition of various stored basic odors $\underline{w}, \underline{w}', \ldots$. In this case the output $y = \underline{w} \cdot \underline{s}$ of neuron v in temporal coding may be interpreted as the amount by which the basic odor $\underline{w}$ (which is stored in the efficacies of the synapses of v) is present in the stimulus $\underline{s}$. Furthermore another neuron $\tilde{v}$ on the next layer might receive as its input $\underline{y} = \langle y, y', \ldots \rangle$ from several such neurons $v, v', \ldots$, i.e. $\tilde{v}$ receives the "mixing proportions" $y = \underline{w} \cdot \underline{s}$, $y' = \underline{w}' \cdot \underline{s}$, for various stored basic odors $\underline{w}, \underline{w}', \ldots$ in temporal coding. This neuron $\tilde{v}$ on the second layer can then continue the pattern analysis by computing for its input $\underline{y}$ the inner product $\underline{W} \cdot \underline{y}$ with some stored "higher order pattern" $\underline{W}$ (e.g. the composition of basic odors that is characteristic for an individual animal). Such multi-layer pattern analysis is facilitated by the fact that the here considered neurons encode their output in the same way in which their input is encoded (in contrast to the approach in Hopfield, 1995).

   One also gets in this way a very fast implementation of Linsker's network (Linsker, 1988) with spiking neurons in temporal coding.

3. For biological neurons it is of course impossible to choose the parameter λ arbitrarily large. On the other hand the experiments of (Bryant and Segundo, 1976) as well as the recent experiments of (Mainen, Sejnowski, 1995) suggest that biological neuron do already exhibit very high precision in their firing times

if the slope of the membrane potential $P_v(t)$ at the time t when it crosses the firing threshold is moderately large.

4. Analog computations with the here considered type of temporal coding become impossible if the jitter in the firing times is large relative to the size of the range $[0, \gamma]$ of analog variables in temporal coding. The following points should be taken into account in this context:

   (a) Even if the jitter is so high that in temporal coding just *two* different outputs can be distinguished in a reliable manner, the computational power of the constructed network $\mathcal{N}$ of spiking neurons is still enormous from the point of view of computational complexity theory. In this case the network can simulate arbitrary *threshold circuits* (i.e. multi-layer perceptrons with heaviside gates) very fast. Threshold circuits are extremely powerful models for parallel digital computation, which can (in contrast to PRAM's and other models for currently available computer hardware) compute various non-trivial boolean functions that depend on a large number n of input bits with polynomially in n many gates and not more than 4 layers (Johnson, 1990, Roychowdhury, 1994, Siu, 1995).

   (b) Formally the value of γ in our preceding construction was required to be very small: it was bounded (according to (8) respectively (9)) by a fraction of the length Δ of the rising segment of an EPSP. However one should keep in mind that we were forced to resort to such small values for γ only because we wanted to prove a rigorous *theoretical* result. The considerations in Remark 1. suggest that in a *practical* context one can still carry out meaningful computations if the linearly rising segments of incoming EPSP are spread out over a somewhat larger time interval than Δ , where they *need no longer overlap*.

   If one wants to compute specific values for the parameters γ respectively Δ , one runs into the problem that the value of Δ varies enormously among different biological neural systems, from about $1 - 3$ ms for EPSP's resulting from AMPA-receptors in cortex to about a second in dark-adapted toad photo-receptors.

   (c) There exists an alternative interpretation of our construction in a biological neural system, which focuses on a smaller spatial scale. In this interpretation a "hot spot" in the dendritic tree of a biological neuron assumes the role of a spiking neuron in our construction. Hot spots are patches of membrane with voltage-dependent channels that are known to occur at branching points of the dendritic tree (Shepherd, 1994, Jaffe, 1992, Mel, 1993, Softky, 1994). They fire a "dendritic spike" if the membrane potential reaches a certain threshold value. From this point of view a *single* biological neuron may be viewed as a "network of spiking neurons", which

according to our construction can simulate in temporal coding a multi-layer sigmoidal neural net. The timing precision of such circuits is possibly very high since it does not involve synapses, see also (Softky, 1994). Furthermore in this interpretation the computation is less affected by possible failures of synapses.

(d) In another biological interpretation one can replace each neuron v in $\mathcal{N}_{N,\varepsilon,\delta}$ by a *pool* P_v of neurons (similarly as in a synfire chain, see Abeles, 1993). The firing time t_v of neuron v is then replaced by the *mean firing time* of neurons in P_v , and an EPSP from v is replaced by a *sum of EPSP's* from neurons in P_v . This interpretation has the advantage that it is less affected by jitter in the firing times of individual neurons, and by stochastic failures of individual synapses. Furthermore the rising segment of a *sum* of EPSP's from P_v is likely to be substantially longer than that of an *individual* EPSP. Hence in this interpretation the parameter γ can be chosen substantially larger than for single neurons.

5. The auxiliary neuron a_0 that provides in our construction a "reference spike" at time T_{in} is not really *necessary*. Without such auxiliary neuron a_0 the "weights" w_i of the inputs s_i are automatically "normalized" so that they sum up to 1 (see (4) with $\sum_{i=0}^{n} w_i$ replaced by $\sum_{i=1}^{n} w_i$). Such normalization is disadvantageous for simulating an arbitrary given sigmoidal gate G , but it may actually be desirable in a biological context.

6. Our construction was based on a specific temporal coding in terms of "reference times" T_{in} and T_{out} . Some biological systems may actually provide such "reference times" that are time-locked with the onset of a sensory stimulus. However our construction can also be adapted to other types of temporal coding that require no "reference times". For example the basic equation (1) at the end of section 1 yields also a mechanism for carrying out analog computations with regard to the scheme of "competitive temporal coding" which is discussed in (Thorpe, 1989). In this coding scheme the firing time t_{a_i} of neuron a_i encodes the analog variable $(t_{a_i} + d_i) - \min_{j=1,\ldots,n} (t_{a_j} + d_j)$, where $d_j := d_{a_j,v}$ is the delay between neuron a_j and v. For $T := \min_{j=1,\ldots,n} (t_{a_j} + d_j)$ we have according to (1)

$$t_v \;=\; \frac{\Theta - BN^-}{\sum_{i=1}^{n} w_i} \;+\; T \;+\; \frac{\sum_{i=1}^{n} w_i \cdot ((t_{a_i} + d_i) - T)}{\sum_{i=1}^{n} w_i} \quad . \tag{10}$$

In this coding scheme the firing time t_v encodes the analog value $t_v - \min_{\tilde{v} \in L} t_{\tilde{v}}$, where L is the layer of neurons to which v belongs. Thus (10) provides the mechanism for computing a segment of a linear function for inputs and outputs in competitive temporal coding. Hence our construction also provides a method

for simulating multi-layer neural nets with regard to this alternative coding scheme. No reference times T_{in} or T_{out} are needed for that.

In this way one can for example inplement a multi-layer pattern analysis as described in Remark 2. without making any use of reference times.

If one wants to simulate gates which employ a *sigmoidal* activation function by spiking neurons with competitive temporal coding, one can add *lateral excitation* among all neurons on the same layer L . In this way the neurons in L are forced to fire within a rather small time window (corresponding to the bounded output range of a sigmoidal activation function). In other applications it appears to be more advantageous to employ instead *lateral inhibition*. This also has the effect of preventing that the value of $t_v - \min_{\tilde{v} \in L} t_{\tilde{v}}$ can become too large.

7. For the sake of simplicity we have considered in the preceding construction only *feedforward* computations on networks of spiking neurons. However one can easily see that the same simulation method can be used to simulate *recurrent* sigmoidal neural nets by *recurrent* networks of spiking neurons. For example one gets in this way a novel implementation of a *Hopfield net* (with synchronous updates). At each "round" of the computation the output of a unit of the Hopfield net is encoded by the firing time of a corresponding spiking neuron *relative* to that of other neurons in the network. For example one may assume that a neuron gives the *highest* possible output value if it is among the *first* neurons which fire at that round. Each spiking neuron simulates in temporal coding a sigmoidal unit, whose inputs are the firing times of the other spiking neurons in the network at the previous round. One can employ here competitive temporal coding (see Remark 6.), hence no reference times or external clock is needed.

   A *stable state* of the Hopfield net is reached in this implementation (with competitive temporal coding) if and only if all neurons fire "regularly", i.e. at regular intervals with a common interspike interval, but in general with different phases. These *phases* encode then the output values of the individual neurons, and together these phase differences represent a "recalled" stored pattern of the Hopfield net. Thus each stored pattern of the Hopfield net is realized by a different assignment of phase differences in some stable oscillation.

   This *novel implementation of a Hopfield net* with spiking neurons in *temporal coding* has apart from its high computation speed another feature that is possibly of biological interest: Whereas the *input* to such network of spiking neuron can be *transient* (encoded in the relative timing of the firing of each neuron in the network at the *first* round), its output is *available over a longer time period*, since it is encoded in the phases of the neurons in a *stable global oscillation* of the network. Hence this implementation makes it possible that even in the rapidly fluctuating environment of temporal coding with single spikes the

outputs from different neural subsystems (which may operate at different time scales) can be collected and integrated by a larger neural system.

3 Universal Approximation Properties of Networks of Noisy Spiking Neurons in Temporal Coding

One of the most interesting and useful features of sigmoidal neural nets N is the fact that if $[0, \gamma]$ is the range of their activation functions, they can approximate for any given natural numbers n and k *any* given continuous function F from $[0, \gamma]^n$ into $[0, \gamma]^k$ within any given $\varepsilon > 0$ (with regard to uniform convergence, i.e. the L_∞-norm). Furthermore it has been shown that it suffices to consider for this purpose feedforward nets N with just one hidden layer of neurons and (roughly) *any* activation function σ which is *not* a polynomial (Leshno et al., 1993). In addition many years of experiments with backprop and other learning rules for sigmoidal neural nets have shown that for most concrete application problems sigmoidal neural nets with relatively *few* hidden units allow a satisfactory approximation of the underlying "target function" F .

The result from the preceding section allows us to transfer these results to networks of spiking neurons with temporal coding. If some feedforward sigmoidal neural net N approximates an arbitrary given continuous function $F : [0, \gamma]^n \to [0, \gamma]^k$ within an ε (with regard to the L_∞-norm), then with probability $\geq 1 - \delta$ the network $\mathcal{N}_{N,\varepsilon,\delta}$ of spiking neurons that we have constructed in section 2 approximates the same F within 2ε (with regard to the L_∞)-norm. Furthermore if N has only a small number p of layers, the computation time of $\mathcal{N}_{N,\varepsilon,\delta}$ can be bounded (for biologically reasonable choices of the parameters involved) by $10 \cdot p$ ms.

Thus if one neglects the fact that the fan-in of biological neurons is bounded by some fixed (although rather large) constant, the preceding theoretical results suggest that networks of biological neurons can (in spite of their "slowness") *approximate* arbitrary continuous functions $F : [0, \gamma]^n \to [0, \gamma]^k$ within any given ε with a computation time of not more than 20 ms.

Finally we would like to point out that our approximation result holds not only for the particular way of encoding analog inputs and outputs by firing times that was considered in the previous section, but basically for *any* coding that is *continuously* related to it. More precisely, let $n, \tilde{n}, k, \tilde{k}$ be arbitrary natural numbers, let $Q : [0, \gamma]^n \to [0, 1]^{\tilde{n}}$ be *any* continuous function that specifies a method of "decoding" $\tilde{n}$ variables ranging over [0,1] from the firing times of n neurons during some time window of length γ (whose endpoint is marked by the firing time of the first one of these n neurons), and let $R : [0, 1]^{\tilde{k}} \to [0, \gamma]^k$ be *any* continuous and invertible function that describes a method for "encoding" $\tilde{k}$ output variables ranging over

[0,1] by the firing times of k neurons during some time window of length γ (whose endpoint is marked by the firing time of the first one of these k neurons). Then for any given continuous function $\tilde{F} : [0,1]^{\tilde{n}} \to [0,1]^{\tilde{k}}$ the composition $F : R \circ \tilde{F} \circ Q$ of these 3 functions is a continuous function from $[0,\gamma]^n$ into $[0,\gamma]^k$. According to our preceding argument there exists a network $\tilde{\mathcal{N}}_{\varepsilon,\delta}$ of noisy spiking neurons (with one "hidden layer") such that for any $\underline{x} \in [0,\gamma]^n$ one has for the output $\tilde{\mathcal{N}}_{\varepsilon,\delta}(\underline{x})$ of this network $\tilde{\mathcal{N}}_{\varepsilon,\delta}$ that $\| F(\underline{x}) - \mathcal{N}_{\varepsilon,\delta}(\underline{x}) \| \leq \varepsilon$ with probability $\geq 1-\delta$, where $\| \cdot \|$ can be any common norm. Hence $\tilde{\mathcal{N}}_{\varepsilon,\delta}$ approximates for arbitrary inputs the given function $\tilde{F} : [0,1]^{\tilde{n}} \to [0,1]^{\tilde{k}}$ for *arbitrarily chosen continuous functions R, Q for coding and decoding of analog variables by firing times of spiking neurons* with a precision of at least $\sup \{\| R^{-1}(\underline{y}) - R^{-1}(\underline{y}') \| : \underline{y}, \underline{y}' \in [0,1]^k \text{ and } \| \underline{y} - \underline{y}' \| \leq \varepsilon\}$. Thus if the inverse R^{-1} of the function R is uniformly continuous, one can approximate $\tilde{F}$ with regard to neural coding and decoding described by R and Q with arbitrarily high precision by networks of noisy spiking neurons with just one hidden layer.

4 Consequences for Learning

In the traditional interpretation of (unsupervised) Hebbian learning a synapse is strengthened if both the presynaptic and the postsynaptic neuron are simultaneously "active" (i.e. both give high output values in terms of their current firing rates). In the implementation of a sigmoidal neural net N by a network of spiking neurons $\mathcal{N}_{N,\varepsilon,\delta}$ in section 2 the "weights" r_i of N are in fact modelled by the "strengths" w_i of corresponding synapses between spiking neurons. However the information whether the presynaptic and postsynaptic neuron both give high output values in *temporal coding* can no longer be read off from their "activity", but only from the *time difference* T_i between their firing times.

This observation gives rise to the question whether there are biological mechanisms known which support a modulation of the efficacy (i.e. "strength") w_i of a synapse in dependence of this time difference T_i . If one works in the "linear range" of the simulation $\mathcal{N}_{G,\varepsilon}$ of a π_γ-gate G according to section 2 (where G computes the function $\langle s_1, \ldots, s_n \rangle \mapsto \sum_{i=1}^n r_i \cdot s_i$) and $h_i(t)$ describes an EPSP, then for Hebbian learning it would be desirable to increase $w_i = \lambda \cdot r_i$ if s_i is close to $\sum_{i=1}^n r_i \cdot s_i$, i.e. if the difference in firing times $T_i := t_v - (T_{in} - s_i) = T_{out} - \sum_{i=1}^n r_i \cdot s_i - T_{in} + s_i$ is close to $T_{out} - T_{in}$. On the other hand one would like to "decrease" w_i if T_i is substantially smaller or larger than $T_{out} - T_{in}$. Hence a Hebbian-style unsupervised learning rule of the form

$$\triangle w_i \;=\; \frac{1}{1 + \beta \cdot (T_i - (T_{out} - T_{in}))^2} - \rho \quad \text{or} \quad \triangle\, w_i \;=\; e^{-\beta (T_i - (T_{out} - T_{in}))^2} - \rho \quad (11)$$

(for suitable parameters $\beta, \rho > 0$) would be meaningful in this context.

Recent results from neurobiology (Stuart and Sakmann, 1994) show that action potentials in neocortical pyramidal cells are actively (i.e. supported by voltage-dependent channels) propagated *backwards* from the soma into the dendrites, see also (Jaffe et al., 1992). Hence the *time difference* T_i between the firing of the presynaptic and the postsynaptic neuron is in principle available to each synapse. Furthermore new experimental results (Markram, 1995, Markram and Sakmann, 1995) show that in vitro the efficacy of synapses of neocortical pyramidal neurons is in fact modulated in dependence of this time difference T_i .

There exists one interesting structural difference between this interpretation of Hebbian learning in temporal coding and its traditional interpretation: the time difference T_i provides a synapse with the full information about the *correlation* between the output values of the pre- and postsynaptic neuron in temporal coding, no matter whether both neurons give high *or* both give low output values. However in the traditional interpretation of Hebbian learning in terms of firing rates the efficacy of a synapse is only increased if both neurons give *high* output values (in frequency-coding).

An implementation of Hebbian learning in the temporal domain (as indicated above) is also appealing in the context of pulse-stream VLSI (i.e. "silicon spiking neurons"). These artificial neural nets are much faster than biological spiking neurons: they can work with interspike intervals in the microsecond range. If for a hardware implementation of a sigmoidal gate with pulse-stream VLSI according to the construction of section 2 a Hebbian learning rule can be applied in the temporal domain after each pulse, such chip may be able to carry out so many learning steps per second, that it could in principle (neglecting I/O constraints) overcome the main impediment of traditional artificial neural nets: their low learning speed.

So far we have assumed in the construction of $\mathcal{N}_{N,\varepsilon,\delta}$ in section 2 that the time delays d_i between the presynaptic neurons a_i and the postsynaptic neuron v (i.e. the time needed until an action potential from a_i can influence the potential at the trigger zone of v) were the same for all neurons a_i . Differences among these delays have the effect of providing an *additive correction* $s_i \mapsto s_i + d_i$ to the variable that is communicated in temporal coding from a_i to v . Hence they also have the ability to give different "weights" to different input variables. In a biological context they appear to be useful for providing to the network "a-priori information" about its computational task, so that Hebbian learning can be viewed as "fine-tuning" on top of this preprogrammed information. If there exist biological mechanisms for modulating such delays (see Hopfield, 1995, Kempter et al., 1996), they would provide in addition to a short term memory via synaptic modulation a separate mechanism for storing and adapting *long term* memory via differences in the delays.

5 Conclusions

We have shown in this article that there exists a rather simple way to compute linear functions and to simulate feedforward as well as recurrent sigmoidal neural nets in temporal coding by networks of noisy spiking neurons. In contrast to the traditionally considered implementation via frequency-coding our new approach yields a computation speed that is by several orders of magnitude faster. In fact, to the best of our knowledge it provides the first theoretical model which is able to explain the experimentally observed speed of fast information processing in the cortex on the basis of relatively slow spiking neurons as computational units.

Further experiments will be needed to determine whether this theoretical model is biologically relevant. One problem is that we do not know in which way *batch*-inputs (consisting of many analog variables *in parallel*) are encoded by biological neural systems. One should note that the existing results on neural coding, see (Rieke et al., 1996), only address the coding of time-series, i.e. of *sequential* analog inputs. However if further experiments would show for example that the input-dependent firing times in visual cortex, as reported in (Bair et al., 1994), vary in a *continuous* (respectively piecewise continuous) manner in response to *smooth* changes of complex inputs, this would provide some support to the here considered style of theoretical models for analog computation with spiking neurons.

Furthermore a biological realization of recurrent neural nets (e.g. Hopfield nets) in temporal coding with spiking neurons, as proposed in Remark 7. in section 2, would predict the occurence of oscillations in neural systems (especially systems involved in pattern recognition and working memory), where the *phase* of individual neurons (or of pools of neurons) with regard to this oscillation is *input-dependent*.

A noteworthly feature of the here presented constructions is that the "weights" (efficacies) of synapses are in principle able to play in *temporal coding* the *same* role as in the more familiar context of *firing rate coding*. Hence all theories and experimental results regarding adaptation of neural circuits via synaptic plasticity can in principle also be applied to such computations in *temporal* coding.

Furthermore a closer look shows that the networks that we have constructed for analog computations in *temporal coding* can compute the *same* analog function also on a different time scale in *firing rate coding*. This possible *dual role* of the here constructed circuits of spiking neurons is of interest in the context of biology. There exists empirical evidence that some neural systems carry out in addition to a very fast "preliminary computation" a more thorough subsequent computation in terms of firing rates, which has the ability to integrate relevant contributions from several neural subsystems, but which takes several hundred ms longer (see, e.g. Heller et al., 1995).

So far it is not known whether there exists a biological neural system whose computational organization can be understood as an implementation of a sigmoidal neural net. However one may argue that this conjecture can be supported by a heuristic "optimality principle" (whereby biological systems often find the theoretically best use for their "hardware"). Feedforward sigmoidal neural nets with few layers are the most powerful and fastest parallel computational model that is known to date, both from the point of view of computational complexity theory and from the point of view of engineering applications. In addition feedforward and recurrent sigmoidal neural nets are the only parallel computational models known which support self-organization (and hence do not require cumbersome and error-prone central "programming"). Hence if the "hardware" of biological neural systems allows in principle an efficient implementation of sigmoidal neural nets, it is not unreasonable to assume that this possibility has been realized by at least some biological neural systems (in spite of our lack of knowledge about the concrete functions which they compute).

Apart from their biological interpretation, the construction of this article appears to be also of interest in the context of hardware implementations of neural nets via pulse-stream VLSI (see e.g. Pratt, 1989, Horinchi et al., 1991, Murray et al., 1994, Jahnke et al., 1995). A simulation of a feedforward sigmoidal neural net by pulse-stream VLSI along the lines of this construction offers the possibility to combine extremely high computation speed (simulating one parallel computation step of the sigmoidal neural net per pulse) with a noise robust and fast transmission of internal analog variables via the relative timing of pulses from different gates. Furthermore an implementation of Hopfield nets according to Remark 7. in section 2 provides a new idea for the technological realization of "content addressable" memory.

We have shown in this article that networks of spiking neurons with temporal coding have *at least* the same computational power as sigmoidal neural nets of roughly the same size and depth. Together with a recent separation result (Maass, 1996b) this implies that networks of spiking neurons have in fact *strictly more* computational power.

Acknowledgement

I would like to thank Martin Arndt, David Haussler, Geoffrey Hinton, John Hopfield, Berthold Ruf, and Gordon Shepherd for stimulating discussions related to the topic of this paper. I also would like to thank the anonymous referees for their helpful comments.

References

Abeles, M., Bergman, H., Margalit, E., and Vaadia, E. (1993) *Spatiotemporal firing patterns in the frontal cortex of behaving monkeys.* J. of Neurophysiology, vol. 70, 1629-1638.

Bair, W., Koch, C., Newsome, W., and Britten, K. (1994) *Reliable temporal modulation in cortical spike trains in the awake monkey.* Proc. of the Symposium on Dynamics of Neural Processing, Washington, USA.

Bialek, W. and Rieke, F. (1992) *Reliability and information transmission in spiking neurons.* Trends in Neuroscience, vol. 15, 428-434.

Bryant, and Segundo, J. P. (1976) J. of Physiology, vol. 260.

Ferster, D. and Spruston, N. (1995) *Cracking the neuronal code.* Science, vol. 270, 756-757.

Gerstner, W. and van Hemmen, J. L. (1994) *How to describe neuronal activity: spikes, rates, or assemblies?* Advances in Neural Information Processing Systems, vol. 6, Morgan Kaufmann (San Mateo) 463-470.

Heller, J., Hertz, J. A., Kjær, T. W., and Richmond, B. J. (1995) *Information flow and temporal coding in primate pattern vision.* J. of Computational Neuroscience, vol. 2(3), 175-193.

Hopfield, J. J. (1991) *Olfactory computation and object perception.* Proc. Nat. Acad. Sci. USA, vol. 88, 6462-6466.

Hopfield, J. J. (1995) *Pattern recognition computation using action potential timing for stimulus representations.* Nature, vol. 376, 33-36.

Horinchi, T., Lazzaro, J., Moore, A., and Koch, C. (1991) *A delay-line based motion detection chip.* Advances in Neural Information Processing Systems, vol. 3, Morgan Kaufmann (San Mateo), 406-412.

Jaffe, D. B., Johnston, D., Lasser-Ross, N., Lisman, J. E., Miyakawa, H., and Ross, W. N. (1992) *The spread of Na^+ spikes determines the pattern of dendritic Ca^{2+} entry into hippocampal neurons.* Nature, vol. 357, 244-246.

Jahnke, A., Roth, U. and Klar, H. (1995) *Towards efficient hardware for spike-processing neural networks.* Proc. of the World Congress on Neural Networks, July 1995 in Washington.

Johnson, D. S. (1990) *A catalog of complexity classes.* In: *Handbook of Theoretical*

Computer Science, vol. A, Leeuwen J.V., ed., MIT Press (Cambridge), 67-162.

Kempter, R., Gerstner, W., van Hemmen, J. L., and Wagner, H. (1996) *Temporal coding in the sub-millisecond range: model of barn owl auditory pathway.* Advances in Neural Information Processing Systems, vol. 8, MIT-Press (Cambridge), to appear.

Leshno, M., Lin, V. Y., Pinkus, A., and Schocken, S. (1993) *Multilayer feedforward networks with a nonpolynomial activation function can approximate any function.* Neural Networks, vol. 6, 861-867.

Linsker, R. (1988) *Self-organization in a perceptual network.* Computer Magazine, vol. 21, 105-117.

Maass, W. (1995) *On the computational power of networks of spiking neurons.* Advances in Neural Information Processing Systems, vol. 7, MIT-Press (Cambridge), 183-190.

Maass, W. (1996a) *On the computational power of noisy spiking neurons.* Advances in Neural Information Processing Systems, vol. 8, MIT-Press (Cambridge), to appear.

Maass, W. (1996b) *Networks of spiking neurons: the third generation of neural network models*, Proceedings of the 7th Australian Conference on Neural Networks 1996 in Canberra, Australia.

Mainen, Z.F. and Sejnowski, T. J. (1995) *Reliability of spike timing in neocortical neurons.* Science, vol. 268, 1503-1506.

Markram, H. (1995) *Neocortical pyramidal neurons scale the efficacy of synaptic input according to arrival time: a proposed selection principle of the most appropriate synaptic information.* Proc. of Cortical Dynamics in Jerusalem, 10-11.

Markram, H. and Sakmann, B. (1995) *Action potentials propagating back into dendrites trigger changes in efficacy of single-axon synapses between layer V pyramidal neurons.* Abstract 788.11 in Vol. 21 of the Proc. of the Conference of the Society for Neuroscience.

Mel, B. W. (1993) *Synaptic integration in an excitable dendritic tree.* J. of Neurophysiology, vol. 70, 1086-1101.

Murray, A. and Tarassenko, L. (1994) *Analogue Neural VLSI: A Pulse Stream Approach.* Chapman & Hall.

Perrett, D. I., Rolls, E. T. and Caan, W. C. (1982) *Visual neurons responsive to faces in the monkey temporal cortex.* Experimental Brain Research, vol. 47, 329-342.

Pratt, G. A. (1989) *Pulse Computation.* Phd-thesis in the Dept. of Elec. Eng. and

Comp. Sci., MIT, Cambridge, USA.

Rieke, F., Warland, D., Ruyter van Steveninck, R., and Bialek, W. (1996) *SPIKES: Exploring the Neural Code.* MIT Press (Cambridge), to appear.

Rolls, E. T. (1994a) *Brain mechanisms for invariant visual recognition and learning.* Behavioural Processes, vol. 33, 113-138.

Rolls, E. T. and Tovee, M. J. (1994b) *Processing speed in the cerebral cortex, and the neurophysiology of visual backward masking.* Proc. Roy. Soc. B., vol. 257, 9-15.

Roychowdhury, V., Siu, K., and Orlitzky, A., eds. (1994) *Theoretical Advances in Neural Computation and Learning*, Kluwer (Boston).

Rumelhart, D. E., Hinton, G. E. and Williams, R. J. (1986) *Learning representations by back-propagating errors.* Nature, vol. 323, 533-536.

Segundo, J.P. (1994) *Noise and the neurosciences: a long history, a recent revival, and some theory.* In: *Origins: Brain and Self Organization*, Pribram, K. H., ed., Lawrence Erlbaum Associates, 300-331.

Sejnowski, T. J. (1995) *Time for a new neural code?* Nature, vol. 376, 21-22.

Shepherd, G. M. (1994) *Neurobiology*, 3rd ed. Oxford University Press (New York).

Siu, K., Roychowdhury, V., and Kalaith, T. (1995) *Discrete Neural Computation*, Prentice Hall (Englewood Cliffs).

Softky, W. (1994) *Sub-millisecond coincidence detection in active dendritic trees.* Neuroscience, vol. 58, 13-41.

Stuart, G. J. and Sakmann, B. (1994). Nature, vol. 267, 69-72.

Thorpe, S. J. and Imbert, M. (1989) *Biological constraints on connectionist modelling.* In: Connectionism in Perspective, Pfeifer, R., Schreter, Z., Fogelman-Soulié, F., and Steels, L., eds., Elsevier (North-Holland).

von Neumann, J. (1956) *Probabilistic logics and the synthesis of reliable organisms from unreliable components.* In: *Automata Studies*, Shannon, C. E., and MacCarthy, J., eds., Princeton University Press.