ALTERNATIVE ENERGY FUNCTIONS FOR OPTIMIZING NEURAL NETWORKS

A. H. Gee & R. W. Prager

CUED/F-INFENG/TR 95

March 1992

Cambridge University Engineering Department
Trumpington Street
Cambridge CB2 1PZ
England

Email: ahg/rwp @eng.cam.ac.uk

Alternative Energy Functions for Optimizing Neural Networks

Andrew H. Gee and Richard W. Prager [1]

Cambridge University Engineering Department
Trumpington Street
Cambridge CB2 1PZ
England

March 1992

Abstract

When feedback neural networks are used to solve combinatorial optimization problems, their dynamics perform some sort of descent on a continuous energy function related to the objective of the discrete problem. For any particular discrete problem, there are generally a number of suitable continuous energy functions, and the performance of the network can be expected to depend heavily on the choice of such a function. In this paper, alternative energy functions are employed to modify the dynamics of the network in a predictable manner, and progress is made towards identifying which are well suited to the underlying discrete problems. This is based on a revealing study of a large database of solved problems, in which the optimal solutions are decomposed along the eigenvectors of the network's connection matrix. It is demonstrated that there is a strong correlation between the mean and variance of this decomposition and the ability of the network to find good solutions. A consequence of this is that there may be some problems which neural networks are not well adapted to solve, irrespective of the manner in which the problems are mapped onto the network for solution.

1 Introduction and Outline

Ever since the Hopfield network was first proposed as a means of solving combinatorial optimization problems [15], researchers have frequently reported disappointment at the failure of the network to find valid solutions, let alone high quality ones [16, 24]. More recently, alternative mappings and modified dynamics have been developed which largely overcome the validity difficulties [3, 20, 23], and neural techniques have been applied with some success to the solution of a wide variety of problems.

Notably successful have been the self-organizing networks, which can be applied to problems with a suitable underlying geometric structure [4, 7, 9], though the neural techniques with the widest applicability are based around the original Hopfield network approach. These techniques invariably perform some kind of descent on a continuous energy function, which coincides with the objective of the combinatorial problem at the valid solution points in the network's output space. Neural techniques, like the Hopfield network or the Mean Field Annealing (MFA) algorithm, perform this descent within a highly parallel framework, which naturally suggests extremely fast, parallel implementations. Their dynamics dictate that the continuous energy function be quadratic in the network's state vector, $\mathbf{v}$. Even with this limitation, there are many problems which can be mapped onto this system, including the benchmark travelling salesman [3, 1, 20] and graph partitioning problems [1, 20, 23], along with more useful problems of two-graph matching [10, 11], scheduling [12], load balancing [8], analogue to digital conversion [22], and a novel implementation of the Viterbi algorithm for Hidden Markov Models [2].

An issue which has aroused little discussion so far concerns the choice of the continuous energy function on which the network performs its descent. For many problems there are an infinite number of quadratic functions which satisfy the condition that they coincide with the combinatorial

[1] Email: ahg/rwp @eng.cam.ac.uk

objective at the valid solution points. While transformations of objective functions have been previously investigated as a means of reducing network costs and mapping a wider variety of problems [18], little attention has been drawn to how the use of these alternative energy functions may affect the solution quality. This issue is addressed in this paper, with specific application to the two-graph matching problem, of which the travelling salesman problem (TSP) is a special case.

In Section 2 we introduce the notation in use throughout the paper, and define some frequently used matrices. Section 3 reviews much of the background to the subject, including the Hopfield and MFA dynamics, and the notion of a valid subspace on which all the valid solution points lie. In Section 4 we recast the entire scenario relative to the basis formed by the eigenvectors of the network's connection matrix; the use of this basis highlights many features of both the network's dynamics and good solutions which would otherwise remain obscured. Section 5 contains a detailed analysis of the network's dynamics relative to this new basis, while Section 6 examines the effect on these dynamics of the various annealing techniques which are often used to improve the network's performance. Included in Sections 4, 5 and 6 are many results taken from [1], which should be referred to for proofs. In Section 7 we introduce a set of alternative energy functions which are all suitable for the solution of the two-graph matching problem, and examine how the use of these functions, coupled with the usual annealing processes, affects aspects of the network's dynamics. Section 8 draws on large databases of solved Euclidean and random TSPs to examine properties of optimal solutions relative to the network's eigenvector basis (by a *random* TSP, we mean a TSP for which the distance matrix does not correspond to any set of points in a 2D plane, but is an arbitrary, symmetric square matrix). The results suggest how a suitable energy function may be selected from among the alternatives for the Euclidean TSPs, but that none of these functions are well suited for the solution of the random problems. A series of experiments, using both the Hopfield and MFA dynamics on the problem databases, confirms these predictions. Finally, in Section 10 we present a discussion of the issues raised in the paper, and draw our conclusions.

2 Notation and Definitions

2.1 Matrix Notation

Let $\mathbf{A}^T$ denote the transpose of $\mathbf{A}$.
Let $[\mathbf{A}]_{ij}$ refer to the element in the i^{th} row and j^{th} column of the matrix $\mathbf{A}$.
Similarly, let $[\mathbf{a}]_i$ refer to the i^{th} element of the vector $\mathbf{a}$.
Sometimes, where the above notation would appear clumsy, and there is no danger of ambiguity, the same elements will be alternatively denoted A_{ij} and a_i.
Let the modulus of an $n \times m$ matrix $\mathbf{A}$ be defined as follows:

$$||\mathbf{A}||^2 = \left[\sum_{i=1}^{n}\sum_{j=1}^{m}[\mathbf{A}]_{ij}^2\right] = \text{trace}\left(\mathbf{A}^T\mathbf{A}\right) \tag{1}$$

Let $\mathbf{A} \otimes \mathbf{B}$ denote the Kronecker product of two matrices. If $\mathbf{A}$ is an $n \times n$ matrix, and $\mathbf{B}$ is an $m \times m$ matrix, then $\mathbf{A} \otimes \mathbf{B}$ is an $nm \times nm$ matrix given by:

$$\mathbf{A} \otimes \mathbf{B} = \begin{bmatrix} A_{11}\mathbf{B} & A_{12}\mathbf{B} & \dots & A_{1n}\mathbf{B} \\ A_{21}\mathbf{B} & A_{22}\mathbf{B} & \dots & A_{2n}\mathbf{B} \\ \dots & \dots & \dots & \dots \\ A_{n1}\mathbf{B} & A_{n2}\mathbf{B} & \dots & A_{nn}\mathbf{B} \end{bmatrix} \tag{2}$$

Let vec($\mathbf{A}$) be the function which maps the $n \times m$ matrix $\mathbf{A}$ onto the nm-element vector $\mathbf{a}$. This function is defined by:

$$\mathbf{a} = \text{vec}(\mathbf{A}) = [A_{11}, A_{21}, \dots, A_{n1}, A_{12}, A_{22}, \dots, A_{n2}, \dots, A_{1m}, A_{2m}, \dots, A_{nm}]^T \tag{3}$$

The following properties of Kronecker products are used in the course of this paper (see [13] for proofs):

$$(\mathbf{A} \otimes \mathbf{B})^T = \mathbf{A}^T \otimes \mathbf{B}^T \tag{4}$$

$$(\mathbf{A} \otimes \mathbf{B})(\mathbf{X} \otimes \mathbf{Y}) \quad = \quad (\mathbf{AX} \otimes \mathbf{BY}) \tag{5}$$

If the $n \times n$ matrix $\mathbf{A}$ has eigenvectors $\{\mathbf{w}_1 \ldots \mathbf{w}_n\}$ with corresponding eigenvalues $\{\gamma_1 \ldots \gamma_n\}$, and the $m \times m$ matrix $\mathbf{B}$ has eigenvectors $\{\mathbf{h}_1 \ldots \mathbf{h}_m\}$ with corresponding eigenvalues $\{\mu_1 \ldots \mu_m\}$, then the $nm \times nm$ matrix $\mathbf{A} \otimes \mathbf{B}$ has eigenvectors $\{\mathbf{w}_i \otimes \mathbf{h}_j\}$ with corresponding eigenvalues $\{\gamma_i \mu_j\}$ $(i \in \{1 \ldots n\}, j \in \{1 \ldots m\})$.

2.2 Some Definitions

Let $\mathbf{I}^n$ be the $n \times n$ identity matrix.
Let $\mathbf{o}^n$ be the n-element column vector of ones:

$$[\mathbf{o}^n]_i = 1 \quad (i \in \{1, \ldots, n\}) \tag{6}$$

Let $\mathbf{O}^n$ be the $n \times n$ matrix of ones:

$$[\mathbf{O}^n]_{ij} = 1 \quad (i, j \in \{1, \ldots, n\}) \tag{7}$$

Similarly, let $\mathbf{O}^{nm}$ be the $n \times m$ matrix of ones.
Let δ_{ij} be the Kronecker impulse function:

$$\delta_{ij} = \begin{cases} 1 & \text{if} \quad i = j \\ 0 & \text{if} \quad i \neq j \end{cases} \tag{8}$$

Let $\mathbf{R}^n$ be the $n \times n$ matrix given by

$$\mathbf{R}^n = \mathbf{I}^n - \tfrac{1}{n}\mathbf{O}^n \tag{9}$$

Multiplication by $\mathbf{R}^n$ has the effect of setting the column sums of a matrix to zero:

$$\begin{aligned} \sum_{i=1}^{n} [\mathbf{R}^n \mathbf{a}]_i &= \sum_{i=1}^{n} [\mathbf{a} - \tfrac{1}{n}\mathbf{O}^n \mathbf{a}]_i = {\mathbf{o}^n}^T [\mathbf{a} - \tfrac{1}{n}\mathbf{O}^n \mathbf{a}] \\ &= {\mathbf{o}^n}^T \mathbf{a} - \tfrac{1}{n}({\mathbf{o}^n}^T \mathbf{o}^n {\mathbf{o}^n}^T)\mathbf{a} = {\mathbf{o}^n}^T \mathbf{a} - {\mathbf{o}^n}^T \mathbf{a} = 0 \end{aligned} \tag{10}$$

Another way of considering $\mathbf{R}^n$ is as a projection matrix which removes the $\mathbf{o}^n$ component from any vector it pre-multiplies, since

$$\mathbf{R}^n \mathbf{o}^n = (\mathbf{I}^n - \tfrac{1}{n}\mathbf{O}^n)\mathbf{o}^n = \mathbf{o}^n - \tfrac{1}{n} n \mathbf{o}^n = \mathbf{0} \tag{11}$$

Also note that since $\mathbf{R}^n$ is a projection matrix, $\mathbf{R}^n \mathbf{R}^n = \mathbf{R}^n$.

3 Background

3.1 The Hopfield Network

A schematic diagram of the continuous Hopfield network [14] is shown in Figure 1. Neuron i has input $[\mathbf{u}]_i$, output $[\mathbf{v}]_i$, and is connected to neuron j with a weight $[\mathbf{T}]_{ij}$. Associated with each neuron is also an input bias term $[\mathbf{i}^{\mathrm{b}}]_i$. The dynamics of the network are governed by the following equations:

$$\dot{\mathbf{u}} = -\eta \mathbf{u} + \mathbf{T}\mathbf{v} + \mathbf{i}^{\mathrm{b}} \tag{12}$$

$$[\mathbf{v}]_i = g([\mathbf{u}]_i) \tag{13}$$

$[\mathbf{v}]_i$ is a continuous variable in the interval 0 to 1, and $g([\mathbf{u}]_i)$ is a monotonically increasing function which constrains $[\mathbf{v}]_i$ to this interval, usually a hyperbolic tangent of the form

$$g([\mathbf{u}]_i) = \frac{1}{1 + \exp(-[\mathbf{u}]_i / T^p)} \tag{14}$$