Neural Networks and Combinatorial Optimization Problems — The Key to a Successful Mapping

(CUED/F-INFENG/TR 77)

Andrew H. Gee, Sreeram V. B. Aiyer and Richard W. Prager [1]

Cambridge University Engineering Department
Trumpington Street
Cambridge CB2 1PZ
England

July 1991

Abstract

For several years now there has been much research interest in the use of Hopfield networks to solve combinatorial optimization problems. Although initial results were disappointing, it has since been demonstrated how modified network dynamics and better problem mapping can greatly improve the solution quality. The aim of this paper is to build on this progress by presenting a new analytical framework in which problem mappings can be evaluated without recourse to purely experimental means. A linearized analysis of the Hopfield network's dynamics forms the main theory of the paper, followed by a series of experiments in which some problem mappings are investigated in the context of these dynamics. In all cases the experimental results are compatible with the linearized theory, and observed weaknesses in the mappings are fully explained within the framework. What emerges is a largely analytical technique for evaluating candidate problem mappings, without having to resort to the more usual trial and error.

1 Introduction and Outline

Ever since the Hopfield network was first proposed as a means of approximately solving NP-complete combinatorial optimization problems [9], there has been considerable research effort to improve the network's performance, which at first was fairly disappointing [18, 10]. Most of this effort has been directed towards improving the reliability with which the network finds valid solutions, while at the same time developing various annealing schedules to help prevent entrapment in local minima of the objective function and force eventual convergence to a hypercube corner. Perhaps the most successful such modification has been the Mean Field Annealing algorithm with neuron normalization [13, 16], which has proved to be very successful with the classic benchmark Travelling Salesman and Graph Partitioning problems [13, 12, 17], as well as with some more practical scheduling problems [6]. The considerable improvement in performance is at the expense of analogue hardware implementability: the Mean Field Annealing dynamics employ a recursive update rule, as well as a neuron normalization division operation, which cannot be performed by the analogue circuit implementation of the original Hopfield network [8]. However, the Mean Field Annealing algorithm is still highly parallel and could greatly benefit from implementation in parallel digital hardware; even when run on conventional serial machines, it remains highly competitive with the other contending optimization techniques [13, 17].

In addition, some researchers have persevered with the original network dynamics, demonstrating that better problem *mapping* can greatly improve the overall quality of solutions. One key step towards this improvement lay in the realization that, for a broad class of problems, all the points in the network's output space corresponding to valid solutions lie on a particular affine subspace [1]. Using this fact, the validity constraints can be grouped together into a single penalty term which

[1] Email: ahg/svb10/rwp @eng.cam.ac.uk

no longer frustrates the optimization objective while the network state vector lies on this 'valid subspace'. The new mapping has been applied with considerable success to the Travelling Salesman problem [1, 2], a point matching problem in pattern recognition [5] and a novel implementation of the Viterbi algorithm for Hidden Markov Models [3].

In this paper, we use the structure of the valid subspace to shed new light on the relationship between the network's dynamics and the problem mapping. In Section 2 we introduce the matrix notation relevant to the rest of the paper. In particular we make extensive use of Kronecker (or Tensor) products [7], which simplify the mapping mathematics considerably. In Section 3 we review the mathematical background of the subject in hand, introducing the form of the valid subspace along the way. Section 4 contains a linearized analysis of the network's dynamics in the context of the valid subspace. We identify a matrix $\mathbf{A}$, the eigenvectors of which are most influential in the convergence of the network's state vector towards a hypercube corner. We also identify a vector $\mathbf{b}$ which is solely responsible for the initial direction of the state vector. In Sections 5 and 6 we test this theory against two different classes of optimization problem, namely the Euclidean Hamilton path problem and the point matching problem. For each case we associate $\mathbf{b}$ with a linear optimization problem, which we call the 'auxiliary linear problem': the relationship between the auxiliary linear problem and the parent optimization problem has considerable bearing on the eventual quality of solutions obtained. In both cases the network's behaviour is found to be as predicted by the theory, and observed shortcomings of the problem mappings are fully explained within this theoretical framework. Section 6 also describes an illustrative experiment in invariant pattern recognition which demonstrates the success of the Hopfield network in solving the point matching problem. Finally, Section 7 presents a brief discussion of the results of the paper, as well as some general conclusions. The Appendices contain ancillary information of relevance to the central material of the paper.

2 Notation and Definitions

2.1 Kronecker Product Notation and Matrix Identities

Let $\mathbf{A}^T$ denote the transpose of $\mathbf{A}$.
Let $[\mathbf{A}]_{ij}$ refer to the element in the i^{th} row and j^{th} column of the matrix $\mathbf{A}$.
Similarly, let $[\mathbf{a}]_i$ refer to the i^{th} element of the vector $\mathbf{a}$.
Sometimes, where the above notation would appear clumsy, and there is no danger of ambiguity, the same elements will be alternatively denoted A_{ij} and a_i.
Let the modulus of an $n \times m$ matrix $\mathbf{A}$ be defined as follows:

$$|\mathbf{A}|^2 = \left[\sum_{i=1}^{n} \sum_{j=1}^{m} [\mathbf{A}]_{ij}^2 \right] = \text{trace}\left(\mathbf{A}^T \mathbf{A}\right) \tag{1}$$

Let $\mathbf{A} \otimes \mathbf{B}$ denote the Kronecker product of two matrices. If $\mathbf{A}$ is an $n \times n$ matrix, and $\mathbf{B}$ is an $m \times m$ matrix, then $\mathbf{A} \otimes \mathbf{B}$ is an $nm \times nm$ matrix given by:

$$\mathbf{A} \otimes \mathbf{B} = \begin{bmatrix} A_{11}\mathbf{B} & A_{12}\mathbf{B} & \ldots & A_{1n}\mathbf{B} \\ A_{21}\mathbf{B} & A_{22}\mathbf{B} & \ldots & A_{2n}\mathbf{B} \\ \ldots & \ldots & \ldots & \ldots \\ A_{n1}\mathbf{B} & A_{n2}\mathbf{B} & \ldots & A_{nn}\mathbf{B} \end{bmatrix} \tag{2}$$

Let $\text{vec}(\mathbf{A})$ be the function which maps the $n \times m$ matrix $\mathbf{A}$ onto the nm-element vector $\mathbf{a}$. This function is defined by:

$$\mathbf{a} = \text{vec}(\mathbf{A}) = [A_{11}, A_{21}, \ldots, A_{n1}, A_{12}, A_{22}, \ldots, A_{n2}, \ldots, A_{1m}, A_{2m}, \ldots, A_{nm}]^T \tag{3}$$

Throughout this paper we make use of the following identities (see [7] for proofs):

$$\text{trace}(\mathbf{AB}) \quad = \quad \text{trace}(\mathbf{BA}) \quad \text{(for } \mathbf{AB} \text{ and } \mathbf{BA} \text{ both square)} \tag{4}$$

$$
\begin{aligned}
(\mathbf{A}\otimes\mathbf{B})^T &= \mathbf{A}^T\otimes\mathbf{B}^T & (5)\\
(\mathbf{A}\otimes\mathbf{B})(\mathbf{X}\otimes\mathbf{Y}) &= (\mathbf{AX}\otimes\mathbf{BY}) & (6)\\
\mathrm{trace}(\mathbf{AB}) &= \left[\mathrm{vec}(\mathbf{A}^T)\right]^T \mathrm{vec}(\mathbf{B}) \quad (\text{for } \mathbf{A} \text{ and } \mathbf{B} \text{ both } n\times n) & (7)\\
\mathrm{vec}(\mathbf{AYB}) &= (\mathbf{B}^T\otimes\mathbf{A})\mathrm{vec}(\mathbf{Y}) & (8)
\end{aligned}
$$

If $\mathbf{w}$ and $\mathbf{x}$ are n-element column vectors, and $\mathbf{h}$ and $\mathbf{g}$ are m-element column vectors, then

$$(\mathbf{w}\otimes\mathbf{h})^T(\mathbf{x}\otimes\mathbf{g}) = (\mathbf{w}^T\mathbf{x})(\mathbf{h}^T\mathbf{g}) \tag{9}$$

If the $n\times n$ matrix $\mathbf{A}$ has eigenvectors $\{\mathbf{w}_1\ldots\mathbf{w}_n\}$ with corresponding eigenvalues $\{\gamma_1\ldots\gamma_n\}$, and the $m\times m$ matrix $\mathbf{B}$ has eigenvectors $\{\mathbf{h}_1\ldots\mathbf{h}_m\}$ with corresponding eigenvalues $\{\mu_1\ldots\mu_m\}$, then the $nm\times nm$ matrix $\mathbf{A}\otimes\mathbf{B}$ has eigenvectors $\{\mathbf{w}_i\otimes\mathbf{h}_j\}$ with corresponding eigenvalues $\{\gamma_i\mu_j\}$ $(i\in\{1\ldots n\}, j\in\{1\ldots m\})$.

2.2 Other Notation and Definitions

Let $\mathbf{I}^n$ be the $n\times n$ identity matrix.
Let $\mathbf{o}^n$ be the n-element column vector of ones:

$$[\mathbf{o}^n]_i = 1 \quad (i\in\{1,\ldots,n\}) \tag{10}$$

Let $\mathbf{O}^n$ be the $n\times n$ matrix of ones:

$$[\mathbf{O}^n]_{ij} = 1 \quad (i,j\in\{1,\ldots,n\}) \tag{11}$$

Let δ_{ij} be the Kronecker impulse function:

$$\delta_{ij} = \begin{cases} 1 & \text{if} \quad i=j \\ 0 & \text{if} \quad i\neq j \end{cases} \tag{12}$$

Let $\mathbf{R}^n$ be the $n\times n$ matrix given by

$$\mathbf{R}^n = \mathbf{I}^n - \tfrac{1}{n}\mathbf{O}^n \tag{13}$$

Multiplication by $\mathbf{R}^n$ has the effect of setting the column sums of a matrix to zero:

$$
\begin{aligned}
\sum_{i=1}^{n}[\mathbf{R}^n\mathbf{a}]_i &= \sum_{i=1}^{n}[\mathbf{a}-\tfrac{1}{n}\mathbf{O}^n\mathbf{a}]_i = \mathbf{o}^{nT}[\mathbf{a}-\tfrac{1}{n}\mathbf{O}^n\mathbf{a}] \\
&= \mathbf{o}^{nT}\mathbf{a} - \tfrac{1}{n}(\mathbf{o}^{nT}\mathbf{o}^n\mathbf{o}^{nT})\mathbf{a} = \mathbf{o}^{nT}\mathbf{a} - \mathbf{o}^{nT}\mathbf{a} = 0 & (14)
\end{aligned}
$$

Another way of considering $\mathbf{R}^n$ is as a projection matrix which removes the $\mathbf{o}^n$ component from any vector it pre-multiplies, since

$$\mathbf{R}^n\mathbf{o}^n = (\mathbf{I}^n - \tfrac{1}{n}\mathbf{O}^n)\mathbf{o}^n = \mathbf{o}^n - \tfrac{1}{n}n\mathbf{o}^n = \mathbf{0} \tag{15}$$

Also note that since $\mathbf{R}^n$ is a projection matrix, $\mathbf{R}^n\mathbf{R}^n = \mathbf{R}^n$.

3 Background and Introduction to the Valid Subspace

A schematic diagram of the continuous Hopfield network [8] is shown in Figure 1. Neuron i has input $[\mathbf{u}]_i$, output $[\mathbf{v}]_i$, and is connected to neuron j with a weight $[\mathbf{T}]_{ij}$. Associated with each neuron is also an input bias term $[\mathbf{i}^{\mathrm{b}}]_i$. The dynamics of the network are governed by the following equations:

$$
\begin{aligned}
\dot{\mathbf{u}} &= -\tfrac{1}{\tau}\mathbf{u} + \mathbf{T}\mathbf{v} + \mathbf{i}^{\mathrm{b}} & (16)\\
[\mathbf{v}]_i &= g([\mathbf{u}]_i) & (17)
\end{aligned}
$$